



# Sparkle Power Inc.

A Leading Power Supply manufacturer  
Web site: [www.sparklepower.com](http://www.sparklepower.com)



## FSP150-50PL1

### 150 Watts Flex ATX Switching Power Supply

#### Features

- Complied with Flex ATX standard
- Active Power Factor Correction Meeting with EN61000-3-2
- High efficiency and reliability
- Remote On/Off function
- Internal 12V DC fan included
- Noise Killer (Thermal fan speed control function)
- Low noise and ripple
- Complies with FCC part 15 subpart J Class B and CISPR 22 Class B
- Output over voltage, short circuit, and over current protection
- 100% Hi-pot, ATE, and burn-in tested
- Re-settable power shut down
- Approved by UL 1950, CSA C22.2 Level 3, TUV EN60950, NEMKO (CB Report), CE

#### Input Characteristics

**Input Range:** 90~265V AC, Full Range Input

**Frequency:** 47~63Hz

**Input Current:** 4A (RMS) @115V AC, 2A (RMS) @230V AC

**Inrush Current:** 50A Max for 115V AC, 80A Max for 230V AC Cold start

#### Specification

- **Temperature Range:** Operating 0° C ~ +35° C on full load; storage & shipping -20° C ~ +80° C
- **Humidity:** 95% on operating and 95% on storage
- **Dielectric Withstand:** Input to frame ground 1800V AC for 1 second
- **Efficiency:** 68% at minimum measured at nominal AC main voltage and frequency with maximum load on all output
- **Rise Time:** Less than 20ms
- **Hold-up Time:** 17ms minimum at nominal input voltage
- **Power Good Signal:** Power on delay time 100 ms to 500 ms, off delay 1ms minimum (TTL and CMOS compatible)
- **Leakage Current:** Not exceed 0.75mA at 115V AC, 60Hz
- **MTBF:** 100,000 hours on maximum load at +25° C degree
- **Dimension (WxHxL):** 81.5x40.5x150mm/3.2"x1.6"x6" inches

#### Output Characteristics

Output Voltage	Minimum Load	Maximum Load	Load Reg.	Line Reg.	Ripple & Noise
+3.3V	0.3A	10.0A	± 5%	± 1%	50mV P-P
+5V	1.0A	14.0A	± 5%	± 1%	50mV P-P
+12V	0.3A	4.2A	± 5%	± 1%	120mV P-P
-12V	0.0A	0.3A	± 10%	± 2%	120mV P-P
+5Vsb	0.0A	2.0 A	± 5%	± 1%	50mV P-P

\*+5V and +3.3V total output not exceed 85W

\*+12V, +3.3V, +5V, and +12V will have the regulation ± 10% when all load take off

#### **Sparkle Power Inc.**

##### **Main Office**

1000 Rock Avenue  
San Jose, CA 95131  
TEL: 408-519-8888  
FAX: 408-519-9999  
E-MAIL: [info@sparklepower.com](mailto:info@sparklepower.com)

#### **Sparkle Power Inc.**

##### **Los Angeles Office**

17071 Green Drive  
City of Industry, CA 91745  
TEL: 626-839-7180  
FAX: 626-839-3395

#### **Sparkle Power Inc.**

##### **Colorado Office**

1316 Indian Paintbrush Lane  
Longmont, CO 80503  
TEL: 303-776-3281  
FAX: 303-776-7645