



Up to 2,000 Watts RF Power for Industrial, Laboratory and Medical Applications.

FEATURING:

- **20 kHz to 1 MHz at greater than 2,000 Watts**
- **Digital Meter, measures forward and reflected power**
- **Front Panel Control of Amplifier and Generator functions**
- **Data acquisition: Status Monitoring & Power Measurement at Analog Port**
- **RS232 communication: Full Control Of Amplifier & Generator Functions**
- **AGC or Power Leveling: Gain Control to better than ± 0.5 dB**
- **Controllable internal DDS signal source**
- **Pulse and Sweep of RF internal signal generator**

Model VTC1757699 is a robust source of RF power for ultrasonic, laser modulation, RFI/EMI, plasma generation, laboratory and general industrial applications. Featuring state-of-the-art design of all amplifier stages and a built-in DDS signal source, it provides everything for a complete and reliable, controlled RF power delivery system. It reflects the Vox ongoing commitment to provide RF power products of the highest quality, incorporating the latest standard for remote control and data acquisition.

OPERATION

The VTC1757699 produces 2,000 Watts of linear power over a frequency range from lower than 20 kHz to over 1 MHz, with low harmonic and intermodulation distortion. It operates without band switching or adjustment. Extended range to over 2 MHz is possible at reduced power. Gain is rated at 63 dB with a typical gain flatness of ± 1.5 dB.

The Front Panel offers a LCD display of Forward, Reflected and Load Power readings, RF Status, MGC/AGC setups and operating frequency when in Generator Mode.

Power meters are calibrated into 50 Ohms and are accurate when operated into a matched load. Outside of matched condition, the mod-



**Power Supply
Front Panel view**

provides an accurate reading of VSWR.

When used as an amplifier, the VTC1757699 is compatible with most signal and function generators, computer synthesizer cards and accurately reproduces all waveforms within its limits.

The Forced-air cooling system and the internal power supply are designed to support operation over most temperature and AC conditions. The unit amplifies the inputs of AM, FM, SSB, pulse and other complex modulations with <-20 dBc (h3) harmonic distortion and output power stability.

OUTPUT PROTECTION

VTC1757699 is protected by its internal control system for 2,000 Watts Forward and 400 Watts Reflected Power. This protects the amplifier output stage from overdrive at the input and extreme mismatch at the Output.

GENERAL

Vox's products are designed to be reliable, compact and light in weight. The use of conservatively rated components ensures high reliability and eliminates the need for periodic calibration.

VTC1757699 Specifications

Class Of Operation Class "B"	Spurious Output - 26 dBm equivalent noise level generated by internal circuits	AC Power Connection See manual for details
Frequency Of Operation 20 kHz to 3 MHz	RF Output Settings & Control - Front Panel EDITOR and function switches for manual control, - RS232 port for GUI or other computer communication. Rear Panel. - SubD 25 Analog and Digital I/O . Port power scale 1V=250W. Rear Panel	AC Input Current (RMS) RF Out nominal 1800W: I ≤ 30A @ 220V RF Out max 2000W: I ≤ 35A @ 220V
RF Power Output 50 Ohm load: Up to 2000W for 20 kHz to 1 MHz Up to 1000W for 1 MHz to 2 MHz Up to 400 W for 2 MHz to 3 MHz Pulse and low duty cycle! Any load: Up to 1800W , continues operation.	BURST operation Pulse range: 1 to 500 usec Period: 1 to 50 milliseconds User settings via GUI and RS232	Cooling Forced air, temperature controlled, heatsink temperature monitored via RS232 GUI interface.
Gain 63 dB @ 2000W / 0.5 MHz ±1.5 dB 20 kHz to 1 MHz	BURST - external DC to > 200 kHz. User defined BURST scheme via SubD-25. See analog port description for more details.	Acoustic level: 45dBa @ Max Fan Speed @ temp.
RF Input Drive for AGC Recommended -5 dBm to 0 dBm for ±0.5 dB gain flatness	SWEEP operation 0.02 to 3MHz. Min time 10 ms, max 10s. Settings and activation from GUI only.	Case Designed to meet EMI and RFI shielding requirements AL chassis, yellow conductive finish. Front & Back Panel: Vox off-white. Cover: Vox black.
Input Drive Source Signal or function generator, analog computer input capable of up to 1 Vp-p @ 50 Ohm Input range: -30 to 0 dBm typical, +5 dBm maximum	Output Blanking For pulsed applications, Vox amplifiers and generators offer blanking of the output signal for minimum noise RF spectrum	Dimensions 405mm x 520 mm x 470 mm (H 16" x W 20.5" x L 18.5")
Internal RF Source DDS oscillator: 20 kHz to 3 MHz, 1 kHz resolution	RF Connectors BNC Female: RF In N Female: RF Out	Weight: 59 kg, 130 lbs.
Input and Output Impedance 50 Ohm 2:1 max INPUT VSWR 3:1 max OUTPUT VSWR	AC Power Source 100 -120 VAC, +/- 10% 200 - 240 VAC, +/- 10%, 47 - 63 Hz,	Mounting Stand alone unit.
Output VSWR Protection 400 W max reflected power limit for Load Impedance > 50 Ohm. Current level protection for Load Impedance < 50 Ohm.		Environmental conditions Temp.: 10° to 35° C ambient Humidity: 80%
Harmonic Level @ 1750W Better then - 13 dBc for 3-d harmonic, any other better then -20 dBc		Equipment intended for ISM applications in laboratory and light industrial

