


# PCLD-8115/8710 Industrial Wiring Terminal With CJC Circuit



## Features

- Low-cost screw-terminal boards
- On-board CJC (Cold Junction Compensation) circuits for direct thermocouple measurement.
- Reserved space for signal-conditioning circuits such as low-pass filter, voltage attenuator and current shunt.
- Industrial-grade screw-clamp terminal blocks for heavy-duty and reliable connections.

### PCLD-8115 only

- Supports PCL-818 series multifunction cards
- Nylon standoffs, screws and washers included for easy mounting
- Dimensions (W x L): 169 x 112 mm (6.7" x 4.4" )

### PCLD-8710 only

- Supports PCI-1710/1710L/1710HG/1710HGL/1711/1711L/1716/1716L cards
- DIN-rail mounting case for easy mounting
- Dimensions (W x L x H): 169 x 112 x 51 mm (6.7" x 4.4" x 2.0")

## Introduction

The PCLD-8115 screw-terminal board offers convenient and reliable signal wiring for multifunction cards with 20-pin flat cable connectors or DB-37 connectors, such as the PCL-818 series cards. PCLD-8710 is designed to match multifunction cards with 68-pin SCSI-II connectors, such as the PCI-1710/1710L/1710HG/1710HGL/1711/1711L/1716/1716L cards.

This screw-terminal board also includes cold junction sensing circuitry that allows direct measurements from thermocouple transducers. Together with software compensation and linearization, every thermocouple type can be accommodated.


Due to its special PCB layout, you can install passive components to construct your own signal-conditioning circuits. So you can easily construct a low-pass filter, attenuator or current shunt converter by adding resistors and capacitors onto the board circuit pads.

## Applications

- Field wiring for analog and digital I/O channels of PC-LabCard™ products.
- Signal conditioning circuits can be implemented as illustrated in the following examples:

### a) Straight-through connection (factory setting)

RA<sub>n</sub> = 0 Ω (short)  
RB<sub>n</sub> = none  
C<sub>n</sub> = none



### b) 1.6 kHz (3dB) low pass filter

RA<sub>n</sub> = 10 KΩ  
RB<sub>n</sub> = none  
C<sub>n</sub> = 0.01 Ω F

$$f_{3dB} = \frac{RB_n}{RA_n + RB_n}$$

### c) 10 : 1 voltage attenuator:

RA<sub>n</sub> = 9 KΩ  
RB<sub>n</sub> = 1 KΩ  
C<sub>n</sub> = none  
Attenuation =  $\frac{RB_n}{RA_n + RB_n}$

(Assume source impedance << 10 KΩ)

### d) 4 ~ 20 mA to 1 ~ 5 V<sub>dc</sub> signal converter:

RA<sub>n</sub> = 0 Ω (short)  
RB<sub>n</sub> = 250 Ω (0.1% precision resistor)  
C<sub>n</sub> = none

## Ordering Information

- **PCLD-8115** Industrial Wiring Terminal Board with CJC circuit and DB-37 cable assembly
- **PCLD-8710** Industrial Wiring Terminal Board with CJC circuit for DIN-rail mounting (cable not included)
- **PCL-10137-1/2/3** DB-37 cable assembly, 1, 2 and 3 m
- **PCL-10168-1/2** 68-pin SCSI-II cable with special shielding for noise reduction, 1 and 2 m

1  
IPPC & AWS

2  
TPC

3  
FPM

4  
ATM

5  
DA&C

6  
cPCI

7  
ADAM-3000

8  
eConnectivity

9  
ICOM

10  
Software

11  
UNO-2000/3000

12  
VBOX

13  
ADAM-4000

14  
ADAM-5000

15  
ADAM-6000

16  
ADAM-8000