

# AR-M9931

Micro Box



## Features

**Fanless Internet Security Platform with Intel Xscale processor with Security Engine, 2WAN, 4LAN, Flash Memory**

Fanless

Intel Xscale

4 LAN

2 WAN

Mini PCI

Xfire.acrosser.com.tw

## Specification

<b>Processor System:</b>		<b>Environment:</b>			
CPU	Xscale Networking Security Processor IXP425 (266MHz)		Operating Temperature	0 ~ 40°C (32 ~ 104°F)	
Speed	266 MHz		Storage Temperature	-20 ~ 70°C (-4 ~ 158°F)	
<b>Memory:</b>		<b>Physical:</b>			
System Memory	Support 64MB, (128MB Option)		Operating Humidity	0 ~ 90% Relative humidity non-condensing	
<b>Ethernet:</b>		Power Requirement		One Power Jack 5V In. (no power button)	
Interface	2 x WAN, 10/100Mbps switch controller for 4 x LAN		Dimension (WxDxH)		225mm x 124mm x 31mm (8.86" x 4.88" x 3.14")
Controller	Realtek 8305C, Realtek 8100B		<b>Ordering Information</b>		
Connector	6 x RJ-45		<b>Standard:</b>		
<b>I/O Interface:</b>		AR-M9931 Fanless Internet Security Platform with Intel IXP425 Processor ULV Celeron CPU , 2WAN, 4LAN, Mini PCI			
	Internal Interface	External Interface			
USB	1 x (USB 2.0 Compliant)				
Serial			2 x RS232 ( 2 x RJ45 Connector)		
Mini PCI Interface	1 (3.3V Mini PCI connector)				
<b>Management:</b>					
Indicator	1xPower LED, 8 LEDs for Network connector as ACT and Link				

Specifications are subject to change without notice.