

Pure Sine Wave Inverters

PST-UL SERIES

Proven extremely reliable in the field for over 10 years. PST's high frequency design provides clean and reliable AC power identical to household electricity. 220 VAC models available by special order.



PST-2000-12

PST-1000-12

PST-12S-12A

Use to operate laptops, portable electronics, small TVs, DVDs, light-duty hand tools and other sensitive electronic devices.

- USB charging port: 5V, 500mA
- Lightweight, portable & compact
- LED indicator
- Temperature controlled fan
- 12V power plug included
- Low idle power draw of less than 0.5 Amps



PST-12S-12A

DC-AC Pure Sine Wave Inverters - PST Series

Model	Input (VDC)	Output (VAC)	Output Power (W)	Surge (W)	Weight (lbs)	Dimensions (inches)	Outlets
PST-12S-12A	12	120	120	-	1.0	7.48 x 4.13 x 1.18	1
PST-15S-12A	12	120	150	300	2.9	8.37 x 5.75 x 2.56	1
PST-300-12	12	120	300	500	3.46	9.69 x 5.76 x 2.58	2
PST-600-12	12	120	600	1000	5.9	10.87 x 9.47 x 3.23	2
PST-1000-12	12	120	1000	2000	8.8	15.63 x 9.47 x 3.23	2
PST-1500-12	12	120	1500	3000	15.6	18.43 x 10.35 x 4.16	2
PST-2000-12	12	120	2000	4000	15.6	18.43 x 10.35 x 4.16	2
PST-300-24	24	120	300	500	3.46	9.69 x 5.76 x 2.58	1
PST-600-24	24	120	600	1000	5.9	10.87 x 9.47 x 3.23	2
PST-1000-24	24	120	1000	2000	8.8	15.63 x 9.47 x 3.23	2
PST-1500-24	24	120	1500	3000	15.6	18.43 x 10.35 x 4.16	2
PST-2000-24	24	120	2000	4000	15.6	18.43 x 10.35 x 4.16	2
RC-15A	Optional remote for 600 and 1000 Watt models. 15' cable. Power ON/OFF						
RC-200	Optional remote for 1500 and 2000 Watt models. 15' cable. Detailed monitoring & remote power operation						